


## 242A Vacuum Tube



### Classification

The No. 242A Vacuum Tube is a three-element tube used as an oscillator, radio-frequency amplifier, modulator or audio-frequency amplifier.

### Base and Socket

The No. 242A Vacuum Tube employs a standard four-prong, bayonet pin type base suitable for use in a Western Electric 112A socket or similar type socket. The arrangement of electrode connections to the base terminals is shown above.

### Ratings and Characteristic Data

Filament Voltage.....	10 Volts
Nominal Filament Current.....	3.25 Amperes
Maximum Plate Voltage.....	1,250 Volts
Maximum Plate Current.....	0.150 Ampere
Average Plate Resistance.....	3,500 Ohms
Average Amplification Factor.....	12.5

#### Approximate Direct Interelectrode Capacities

Plate to Grid.....	13.0 MMF
Plate to Filament.....	4.0 MMF
Grid to Filament.....	6.5 MMF

#### Audio-Amplifier or Modulator Rating—Peak Grid Drive equal to or less than the Bias—Class A Service


Maximum Plate Voltage.....	1000
Maximum Plate Current.....	0.85 Ampere
Maximum Plate Dissipation.....	85 Watts
Grid Bias Voltage.....	—50 Volts
Load Impedance.....	7,000 Ohms
Undistorted Output.....	10 Watts

**Radio-Frequency Amplifier**—Grid Bias practically at Cut-Off, Grid Drive higher than the Bias—Class B Service

Maximum Plate Voltage.....	1,250
Maximum Plate Current.....	0.150 Ampere
Maximum Plate Dissipation.....	100 Watts
Grid Bias Voltage.....	—100 Volts
Peak Output.....	125 Watts

**Oscillator or Radio-Frequency Amplifier**—Grid Bias below Cut-Off—Class C Service

Maximum Modulated Plate Voltage (DC).....	1,000 Volts
Maximum Non-modulated Plate Voltage (DC).....	1,250 Volts
Maximum Plate Current.....	0.150 Ampere
Maximum Plate Dissipation.....	100 Watts
Maximum Radio-Frequency Charging Current in Grid and Plate Leads.....	5 Amperes
Approximate Grid Bias.....	—150 Volts
Maximum Output.....	125 Watts



**Average Static Characteristics**

The accompanying curves give the average static characteristics of the No. 242A Vacuum Tube. These curves are taken with the filament operating on alternating current and with the plate and grid returns connected to a center point of the filament transformer.


**General Features**

The No. 242A Vacuum Tube has an unusually rugged type of structure which insures against breakage in shipment and in service and makes possible the maintenance of uniform electrical characteristics.

The manufacturing process control, long aging together with an adequate thoriated tungsten filament, insure this tube of electrical stability and extremely long life when operated under rated conditions.

## *Western Electric*

### 242A Vacuum Tube



**Classification—Filamentary air-cooled triode**

May be used as an audio-frequency amplifier or as a radio-frequency amplifier, modulator or oscillator.

**Dimensions—**Dimensions and outline diagrams are shown in Figures 1 and 2. The overall dimensions are:

Maximum overall length.....	7 <sup>15</sup> / <sub>16</sub> "
Maximum diameter.....	2 <sup>5</sup> / <sub>16</sub> "

**Mounting—**Large four-pin bayonet base for use in a W.E. 112A or similar socket, for either vertical or horizontal mounting. If mounted horizontally the plane of the filament, which is indicated in Figure 2, should be vertical.

**Filament**—Thoriated tungsten.

Filament voltage.....	10 volts a.c. or d.c.
Nominal filament current.....	3.25 amperes
Average thermionic emission.....	1.5 amperes

**Average Direct Interelectrode Capacitances**

Plate to grid.....	13.0 $\mu\mu\text{f}$
Grid to filament.....	6.5 $\mu\mu\text{f}$
Plate to filament.....	4.0 $\mu\mu\text{f}$

**Characteristics**—Performance data given below are based upon a typical set of conditions. Variations can be expected with different circuits and tubes.

Figures 3 and 4 give the static characteristics of a typical tube plotted against grid and plate voltages.

**Average Characteristics** at maximum direct plate voltage and dissipation—Class A ( $E_b = 1250$  volts,  $I_b = 60$  milliamperes)

Amplification factor.....	12.5
Plate resistance.....	3500 ohms
Grid to plate transconductance.....	3600 micromhos

**Operation****Maximum Ratings**

Max. direct plate voltage.....	1250 volts
Max. direct plate current.....	150 milliamperes
Max. plate dissipation.....	85 watts
Max. direct grid current.....	50 milliamperes
Max. r-f grid current.....	5 amperes
Max. frequency for the above ratings.....	6 megacycles
Max. plate voltage for upper frequency limit of 30 Mc.....	600 volts
Max. plate voltage for frequencies between 6 and 30 Mc in proportion.	

**Class A Audio Amplifier or Modulator**

Direct plate voltage.....	1250	1000	750 volts
Grid bias.....	-70	-46	-25 volts
Direct plate current.....	60	75	100 milliamperes
Plate dissipation.....	75	75	75 watts
Load impedance.....	10,000	7000	6000 ohms
Undistorted output.....	18.0	12.0	5.0 watts

**Class B Audio Amplifier or Modulator** for balanced 2 Tube Circuit

Direct plate voltage.....	1250	1000 volts
Grid bias.....	-80	-55 volts
Direct plate current per tube		
No drive.....	30	30 milliamperes
Max. drive.....	150	150 milliamperes
Plate dissipation.....	80	70 watts
Load resistance, plate-to-plate.....	8000	6000 ohms
Load resistance, per tube.....	2000	1500 ohms
Approximate maximum output—2 tubes.....	200	165 watts
Recommended power for driving stage.....	25	25 watts

**Class B Radio-Frequency Amplifier**

Direct plate voltage.....	1250	1000 volts
Direct plate current for carrier conditions.....	106	130 milliamperes
Grid bias.....	-90	-70 volts
Approx. carrier watts for use with 100% modulation..	44	43 watts

**Class C Radio-Frequency Oscillator or Power Amplifier—Unmodulated**

Direct plate voltage.....	1250	1000 volts
Direct plate current.....	150	150 milliamperes
Grid bias.....	-150 to -200	-120 to -160 volts
Nominal power output.....	130	100 watts
Plate dissipation.....	57.5	50 watts

**Class C Radio-Frequency Amplifier—Plate Modulated**

Direct plate voltage.....	1000	750 volts
Direct plate current.....	150	130 milliamperes
Grid bias.....	-160	-120 volts
Max. direct grid current.....	50	50 milliamperes
Nominal carrier power output for use with 100% modulation.....	100	65 watts

**Operating Precautions**

**Mechanical**—Figures 1 and 2 show the overall dimensions and basing arrangement for the tube.

The tubes should not be subjected to mechanical shock or excessive vibration. Mechanical vibration may cause breakage of the thoriated tungsten filaments.

A free circulation of air must be provided to insure adequate cooling of the glass during operation.

**Electrical**—Overload protection should always be provided for the plate circuit. A suitable fuse or circuit breaker should remove the plate voltage if the plate current exceeds 175 milliamperes. Although the tube is sufficiently rugged to withstand momentary overloads, a prolonged overload caused by inefficient adjustment of the circuit, may damage the tube. When adjusting a new circuit, reduced plate voltage or a series resistance of 1000 to 5000 ohms in the plate circuit should be used until it is operating properly.

The filament should always be operated at the rated voltage, measured at the tube terminals. A 5% decrease in filament voltage reduces the thermionic emission approximately 25%. Either direct or alternating current may be used for heating the filament. If direct current is used, the plate and grid circuit returns should be connected to the negative filament terminal. If alternating current is used, the circuit returns should be connected to the center tap of the filament heating transformer winding or to the center tap of a resistor placed between the filament terminals. A resistance of 20 to 30 ohms of three watt rating is suitable.

In cases where severe and prolonged overload has temporarily impaired the electronic emission of the filament, the activity may be restored by operating the filament, with the plate and grid voltages off, 30% above normal voltage for 10 minutes followed by a longer period at normal voltage.

### **Audio Amplifier or Modulator**

**Class A**—Peak grid drive equal to or less than the grid bias.

Grid bias may be obtained from the drop across a resistance in the plate current return or from a battery or rectifier supply.

Plate dissipation allowable for this type of service is generally lower than is safe for other uses since the energy is dissipated in the plate in smaller areas due to relatively high voltage drop in the tube.

The plate dissipation is equal to the plate voltage multiplied by the normal plate current. Performance data is based upon the use of a resistance load. Undistorted output is calculated on the basis of 5% second harmonic distortion.

**Class B**—Grid bias practically at cut-off and grid driving voltage higher than the bias.

Two tubes may be used in a balanced circuit. An adequate driving stage and an input transformer with good regulation must be used so that the grid current drawn during positive grid swings does not produce appreciable distortion. The output transformer must transform the load impedance to the proper value for the tubes used. The power output obtainable will be determined by the quality of the transformer used and the amount of distortion which can be tolerated. The grid bias must be held constant and therefore cannot be obtained by grid leak or series resistor methods. A battery or other source having good regulation is necessary.

The power required of a modulator for complete modulation of a Class C amplifier is one-half the direct power input to the plates of the Class C amplifier.

### **Radio-Frequency Oscillator or Power Amplifier**

**Class B**—Radio-Frequency Amplifier

The Class B radio-frequency amplifier is used to amplify a modulated radio-frequency carrier wave without appreciable distortion. It operates similarly to the Class B audio amplifier except that a single tube may be used, the tuned output circuit serving to preserve the wave shape. The push-pull circuit, however, eliminates the even order harmonics and thus increases the efficiency slightly.

**Class C**—Radio-Frequency Oscillator or Power Amplifier—Grid bias below cut-off.

#### **Unmodulated**

This type of operation is suitable for telegraphy, or the production of a continuous flow of radio-frequency power for purposes other than communication.

**Plate Modulated**

This type of operation is for use when the modulating voltage is superimposed on the plate supply voltage and to obtain good quality the output power should vary as the square of the plate voltage. For complete or 100% modulation, the plate voltage varies from zero to twice the applied direct value during a cycle of the audio frequency. With no modulation applied, the plate voltage is, of course, the direct value and the carrier power output is one-fourth of the peak power output under 100% modulation. In this case, since the plate voltage varies with modulation, the direct value must be rated lower than for other types of operation.

**High Frequency Ratings**

The frequency limits specified under maximum ratings are based on the tube being used as an oscillator. The tube may be used at full rating up to 6 megacycles. When operating at higher frequencies, the dielectric losses, charging currents and lead-in heating are increased greatly. The plate voltage and hence plate dissipation must be reduced to values specified for the upper frequency limit and for frequencies between these two limits the plate voltage should be proportionately reduced.




FIG. 1




FIG. 2




FIG. 3




FIG. 4